



VHF AND UHF TRANSCEIVERS

**IC-F3003**

VHF transceiver

**IC-F4003**

UHF transceiver

## Affordable, high performance radio that offers abundant features

### Simple operation for instant communication

The IC-F3003 series is so easy to use there's no special training required. The few knobs and buttons are generously sized for easy operation and are designed to provide non-slip, positive action – even while wearing gloves.

### Easy to hear in noisy areas

The built-in bridge-tied load (BTL) amplifier offers powerful 800 mW\* audio output from the large 45 mm speaker. The radio delivers loud and intelligible audio even in noisy environments.

\* Typical with internal speaker

### Longer operating time

A new high efficiency FET of the IC-F3003 series reduces consumption current and provides 20 hours\* of operating time with the BP-265, 2000 mAh battery pack. Even when used with the BP-264, the radio offers 14 hours\* of operating time.

\*Tx:Rx:Standby=5:5:90. Power save function ON.

### Weather resistant, dust protection, military rugged

While the radio is a compact unit with a height of only 111 mm, the radio is tested to dust protection and water resistant equivalent to IP54 and 11 categories of MIL-STD-810 environmental test. In short, the IC-F3003 series is built rugged!

### Internal VOX capability for hands-free operation

The radio has the internal VOX capability for hands-free operation. Optional compatible headset with plug adapter cable OPC-2004LA can be used with the radio. Also, the VOX gain and VOX delay time are adjustable.

### Selective calling, quiet stand-by and more

2-Tone and 5-Tone signalings give you selective calling, quiet stand-by and other convenient functions with programming. The radio "stun" function disables a radio over the air and the "revive" function restores the stunned radio.

### Scan features

The priority scan allows you to monitor one or two priority channels while scanning other non-priority channels. The Tx channel and talk back functions allow you to make a quick response while scanning.

### Other features

- DTMF autodial
- CTCSS/DTCSS encoder/decoder
- BIIS PTT ID transmission
- MDC PTT ID and emergency
- Low battery alert
- 2-step power save
- PC programmable
- Time out timer
- Talk around function
- Lone worker function
- Enhanced emergency
- 3-color LED
- Surveillance function



Dust Protection



Water Resistance



Limited functions.

**SPECIFICATIONS**

	IC-F3003	IC-F4003
<b>GENERAL</b>		
Frequency coverage	136–174 MHz	350–400 MHz 400–470 MHz 450–520 MHz
Number of channels	16 channels	
Type of emission	16K0F3E/11K0F3E	
Channel spacing	12.5/25 kHz	
PLL channel step	2.5/3.125 kHz	5/6.25 kHz
Power supply requirement	7.2 V DC nominal	
Current drain (approx.)		
Tx High	1.3 A	1.3 A
Rx Max. audio	330 mA (Internal SP)	330 mA (Internal SP)
Standby	75 mA	70 mA
Antenna impedance	50 Ω	
Operating temperature range	–30°C to +60°C (Radio only)	
Dimensions (WxHxD)	58x111x31.0 mm (With BP-264)	
(Projections not included)	58x111x35.5 mm (With BP-265)	
Weight (approx.)	330 g (With BP-264)	270 g (With BP-265)
<b>TRANSMITTER</b>		
Output power (at 7.2 V DC)	5 W, 2 W, 1 W (Hi, L2, L1)	4 W, 2 W, 1 W (Hi, L2, L1)
Max. frequency deviation	± 5.0 kHz/±2.5 kHz (Wide/Narrow)	
Frequency stability	±2.5 ppm	
Spurious emissions	70 dB min.	
FM Hum and noise	46/40 dB typ. (Wide/Narrow)	
Audio harmonic distortion (AF 1 kHz 40% deviation)	1.0%/1.5% typ. (Wide/Narrow)	
Ext. microphone connector	3-conductor 2.5 (d) mm (1/10")/2.2 kΩ	
<b>RECEIVER</b>		
Sensitivity (at 12 dB SINAD)	0.25 μV typ.	
Adjacent channel selectivity	78/70 dB typ. (W/N)	73/65 dB typ. (W/N)
Spurious response rejection	70 dB min.	
Intermodulation rejection	75 dB typ.	74 dB typ.
Hum and noise (Without CCITT filter)	54/50 dB typ. (W/N)	52/47 dB typ. (W/N)
Audio output power		
Internal SP (With 12 Ω load)	800 mW typ. (at 5% distortion)	
External SP (With 8 Ω load)	400 mW typ. (at 5% distortion)	
Ext. speaker connector	2-conductor 3.5 (d) mm (1/8")/8 Ω	

All stated specifications are subject to change without notice or obligation.

**Applicable U.S. Military Specifications & IP Rating**

Standard	MIL 810F	
	Method	Procedure
Low Pressure	500.4	I, II
High Temperature	501.4	I, II
Low Temperature	502.4	I, II
Temperature Shock	503.4	I
Solar Radiation	505.4	I
Rain Blowing/Drip	506.4	I, III
Humidity	507.4	–
Salt Fog	509.4	–
Dust Blowing	510.4	I
Vibration	514.5	I
Shock	516.5	I, IV

Also meets equivalent MIL-STD-810-C, -D and -E.

Ingress Protection Standard	
Dust & Water	IP54 (Dust-protection and water resistant)

**OPTIONS**

Some options may not be available in some countries. Please ask your dealer for details.

Battery packs	Type and capacity	Operating time* (Approx.)
BP-263	AA (LR6) batteries x 6	–
BP-264	Ni-MH, 7.2 V 1400mAh	14 hours
BP-265	Rechargeable Li-ion, 7.4 V 1900 mAh (min.) 2000 mAh (typ.)	20 hours

\* Tx: Rx: standby = 5:5:90. Power save function ON.

**REGULAR CHARGER**  
For BP-264 (Ni-MH battery)



BC-147S/BC-206S\*1 BC-192

Charges the BP-264 in 16 hours (approx.).

**RAPID CHARGER**  
For BP-264 (Ni-MH battery)



BC-123S\*2 BC-191

Charges the BP-264 in 2 hours (approx.).

**RAPID CHARGER**  
For BP-265 (Li-ion battery)



BC-123S\*2 BC-193

Charges the BP-265 in 2.5 hours (approx.).

\*1 BC-147SA for USA plug. SV for Australia plug. BC-206SE for Europe plug. \*2 BC-123SA for USA plug. SE for Europe plug. SV for Australia plug.

**MULTI-CHARGER**  
For BP-264/BP-265



BC-197

**CIGARETTE LIGHTER CABLE & POWER SUPPLY CABLES**



CP-23L For use with BC-191 or BC-193

OPC-515L For use with BC-191, BC-192 or BC-193

OPC-656 For use with BC-197

**CHARGER BRACKET**



MB-130 For use with BC-191, BC-192, BC-193

**SPEAKER-MICROPHONES**




HM-158LA HM-159LA

**BELT CLIP**



MB-124 Alligator type Same as supplied.

**HEADSETS**




HS-94 Earhook type

HS-95 Behind-the-head type

HS-97 Throat type

Either VS-4LA or OPC-2004LA is required when using any of headsets.

**PTT SWITCH CABLE and PLUG ADAPTER CABLE**



VS-4LA For manual PTT operation

OPC-2004LA For VOX operation

- STANDARD ANTENNAS**

  - FA-SC25V : 136–150 MHz
  - FA-SC55V : 150–174 MHz
  - FA-SC25U : 400–430 MHz
  - FA-SC57U : 430–470 MHz
  - FA-SC72U : 470–520 MHz
  - FA-SC01U : 350–400 MHz

**CUT ANTENNAS**

  - FA-SC61VC : 136–174 MHz
  - FA-SC61UC : 380–520 MHz

**HIGH GAIN ANTENNAS**

  - FA-SC62V : 150–160 MHz
  - FA-SC63V : 155–165 MHz

**STUBBY ANTENNAS**

  - FA-SC56VS : 150–162 MHz
  - FA-SC57VS : 160–174 MHz
  - FA-SC73US : 450–490 MHz

**CHARGER ADAPTERS**

  - AD-120 for BP-264
  - AD-121 for BP-265

Either AD-120 or AD-121 charger adapters are supplied with the BC-197, depending on BC-197's version.

Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in Japan, the United States, the United Kingdom, Germany, France, Spain, Russia, Australia, New Zealand and/or other countries. All trademarks are the properties of their respective holders.

**Icom Inc.** 1-1-32, Kamiminami, Hirano-Ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

[www.icom.co.jp/world](http://www.icom.co.jp/world)

**Count on us!**

Your local distributor/dealer:

**Icom America Inc.**  
12421 Willows Road NE,  
Kirkland, WA 98034, U.S.A.  
Phone: +1 (425) 454-8155  
Fax: +1 (425) 454-1509  
E-mail: sales@icomamerica.com  
URL: <http://www.icomamerica.com>

**Icom (Europe) GmbH**  
Communication Equipment  
Auf der Krautweide 24  
65812 Bad Soden am Taunus, Germany  
Phone: +49 (6196) 76685-0  
Fax: +49 (6196) 76685-50  
E-mail: info@icomeurope.com  
URL: <http://www.icomeurope.com>

**Icom France s.a.s.**  
Zac de la Plaine,  
1 Rue Brindejone des Moulinais, BP 45804,  
31505 Toulouse Cedex 5, France  
Phone: +33 (5) 61 36 03 03  
Fax: +33 (5) 61 36 03 00  
E-mail: icom@icom-france.com  
URL: <http://www.icom-france.com>

**Icom Canada**  
Glenwood Centre #150-6165  
Highway 17A, Delta, B.C.,  
V4K 5B8, Canada  
Phone: +1 (604) 952-4266  
Fax: +1 (604) 952-0090  
E-mail: info@icomcanada.com  
URL: <http://www.icomcanada.com>

**Icom Spain S.L.**  
Ctra. Rubi, No. 88 "Edificio Can Castanyer"  
Bajos A 08174, Sant Cugat del Valles,  
Barcelona, Spain  
Phone: +34 (93) 590 26 70  
Fax: +34 (93) 589 04 46  
E-mail: icom@icomspain.com  
URL: <http://www.icomspain.com>

**Icom (Australia) Pty. Ltd.**  
Unit 1 / 103 Garden Road,  
Clayton, VIC 3168 Australia  
Phone: +61 (03) 9549 7500  
Fax: +61 (03) 9549 7505  
E-mail: sales@icom.net.au  
URL: <http://www.icom.net.au>

**Icom Brazil**  
Rua Itororó, 444 Padre Eustáquio  
Belo Horizonte MG,  
CEP: 30720-450, Brazil  
Phone: +55 (31) 3582 8847  
Fax: +55 (31) 3582 8987  
E-mail: sales@icombrasil.com

**Icom (UK) Ltd.**  
Blacksole House, Altira Park,  
Herne Bay, Kent, CT6 6GZ, U.K.  
Phone: +44 (0) 1227 741741  
Fax: +44 (0) 1227 741742  
E-mail: info@icomuk.co.uk  
URL: <http://www.icomuk.co.uk>

**Shanghai Icom Ltd.**  
No.101, Building 9, Caifuxingyuan Park,  
No.188 Maoting Road, Chedun Town,  
Songjiang District, Shanghai, 201611, China  
Phone: +86 (021) 6153 2768  
Fax: +86 (021) 5765 9987  
E-mail: bjicom@bjicom.com  
URL: <http://www.bjicom.com>