



VHF AND UHF DIGITAL TRANSCEIVERS

IC-F3360DT

VHF Transceiver with Full Keypad

IC-F4360DT

UHF Transceiver with Full Keypad

IC-F3360DS

VHF Transceiver with Simple Keypad

IC-F4360DS

UHF Transceiver with Simple Keypad

Ready for NXDN™ Type-C Trunking with Superior Waterproof Protection



IDAS™ ICOM DIGITAL ADVANCED SYSTEM

Type-C Trunking Compatible

The IC-F3360D series provides NXDN™ Type-C trunking and NXDN™ conventional systems.

- Paging call
- All call
- Individual call
- Text message
- Stun, Kill and Revive (RX)
- Over-the-air alias
- 15-bit digital scrambler
- Mixed mode operation (Conventional system)
- Broadcast call
- Group call
- Status call
- Emergency call
- Radio check (RX)
- GPS
- RAN

Menu-driven User Interface

The menu-driven user interface provides easy and intuitive operation. The functions can be toggled with the left and right [P2] and [P3] buttons and allow you to perform various operations and settings.



Built-in GPS Receiver

Your current position data can be attached to a voice or data (status or emergency signal) transmission and can be sent to dispatch stations.

Man Down & Lone Worker

The man down function sends an emergency signal if left in a horizontal position. The lone worker function detects if the transceiver is not operated or not moved for a preset period.

Transparent Data

When IC-F3360D series is connected to a PC or other external equipment, the transparent data function allows data communication in a digital mode.

IP67 Dust-tight & Waterproof

The IC-F3360D series provides rugged protection against dust and water. The transceiver can withstand 1 m depth of water for 30 minutes.

800 mW (typ.) Audio Output

The built-in BTL amplifier doubles the audio output power and the large 40 mm speaker delivers loud 800 mW (typ.) audio to receive all calls under noisy environments.

Other Features

- 512 memory channels with 128 zones
 - CTCSS/DTCS/DTMF encoder/decoder*
 - MDC 1200 PTT ID transmission*
 - Inversion voice scrambler*
 - Audio compander*
- (* = Analog mode only)



IC-F3360DT

IC-F4360DS

SPECIFICATIONS

	IC-F3360DT/DS	IC-F4360DT/DS
GENERAL		
Frequency coverage	136–174 MHz	400–470 MHz
Number of channels	512 channels/128 zones	
Type of emission	8K50F3E, 8K30F1E/F1D, 4K00F1E/F1D	
Channel spacing	15/12.5/6.25 kHz	
Power supply requirement	7.5 V DC nominal	
Current drain (approximate)		
Tx High (at 5 W)	1.5 A	1.8 A
Rx Rated output/Standby	550 mA/140 mA	550 mA/140 mA
Antenna impedance	50 Ω	
Operating temperature range	–30 °C to +60 °C; –22 °F to +140 °F (Radio specifications)	
Dimensions (W×H×D)	53.5 × 142.7 × 39.5 mm; 2.1 × 5.6 × 1.6 in (Projections not included)	
Weight (approximate)	400 g; 14.1 oz (With BP-232WP, MB-94R & FA-SC57U)	

TRANSMITTER		
Output power (at 7.5 V DC)	5 W, 1 W (Hi, Low)	
Max. frequency deviation	±2.5 kHz (Narrow)	
Frequency stability	±1.0 ppm	
Spurious emissions	75 dB typ.	
FM Hum and noise	50 dB typ. (Narrow)	45 dB typ. (Narrow)
Audio harmonic distortion	1.5% typ. (AF 1 kHz 40% deviation)	
FSK error	1% typ. (Digital 6.25/12.5 kHz)	
Ext. microphone connector	14-pin multi-connector/2.2 kΩ	

RECEIVER		
Sensitivity (Analog 12 dB SINAD)	0.24 μV typ.	
(Digital 5% BER)	–8.0 dBμV emf typ. (0.20 μV typ.)	
Adjacent channel selectivity	68/67/59 dB typ. (Narrow/D 12.5 kHz/D 6.25 kHz)	
Spurious response rejection	80 dB typ.	
Intermodulation rejection	75/70/70 dB typ. (Narrow/D 12.5 kHz/D 6.25 kHz)	
Hum and noise	50 dB typ. (Narrow)	48 dB typ. (Narrow)
Audio output power	800 mW typ. (Internal SP, 12 Ω load)	
(at 5% distortion)	1000 mW typ. (External SP, 8 Ω load)	
External speaker connector	14-pin multi-connector/8 Ω	

Measurements made in accordance with TIA-603, EN 301-166 and EN 300-113. All stated specifications are subject to change without notice or obligation.

Applicable U.S. Military Specifications & IP Rating

Standard	MIL 810G	
	Method	Procedure
Low Pressure	500.5	I, II
High Temperature	501.5	I, II
Low Temperature	502.5	I, II
Temperature Shock	503.5	I-C
Solar Radiation	505.5	I
Rain Blowing/Drip	506.5	I, III
Humidity	507.5	II
Salt Fog	509.5	–
Dust Blowing	510.5	I
Immersion	512.5	I
Vibration	514.6	I
Shock	516.6	I, IV

Also meets equivalent MIL-STD-810-C, -D, -E and -F.

Ingress Protection Standard (IC-F3360D/F4360D, BP-232WP and HM-184/H)	
Dust & Water	IP67 (Dust-tight and waterproof protection)

Supplied accessories: (May differ according to version)
 • Battery pack, BP-232WP • Belt clip, MB-94R • Antenna

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.

BATTERY PACK AND CASES

BP-232WP BP-240 BP-261

Battery packs	Type	Capacity	Operating time*
BP-232WP	Rechargeable Li-ion battery	2250 mAh (min.), 2300 mAh (typ.)	14.5 hours (D) 13 hours (A)
BP-240	LR03 (AAA) batteries × 6	–	–
BP-261	LR6 (AA) batteries × 6	–	–

* Approx. Tx: Rx: standby = 5:5:90. Power save function is set to "Short".
 D means Digital mode, A means Analog mode.

REGULAR CHARGER

BC-171
BC-147SA/SV

Charges the BP-232WP in 8–10 hours (approx.).

RAPID CHARGER

BC-160
BC-123SA

Charges the BP-232WP in 3 hours (approx.).

MULTI-CHARGER

BC-197 BC-157S

Charges up to six BP-232WP battery packs in 3.5 hours (approx.).

SPEAKER-MICROPHONE

HM-184/H

HEADSETS and PTT SWITCH CABLE

HS-94 Earhook type
HS-95 Behind-the-head type
HS-97 Throat type
VS-4MC Required when using any of these headsets

BELT CLIPS

MB-93 MB-94R

LEATHER BELT HANGERS

MB-96N MB-96F MB-96FL

CHARGER BRACKET

MB-130
For use with BC-160

CIGARETTE LIGHTER CABLE & POWER SUPPLY CABLE

CP-23L For use with BC-160
OPC-656 For use with BC-197

ACC ADAPTOR

AD-118
For use with Hirose plug accessory

- ANTENNAS**
- FA-SC25V: 136–150 MHz
 - FA-SC55V: 150–174 MHz
 - FA-SC25U: 400–430 MHz
 - FA-SC57U: 430–470 MHz
 - FA-SC72U: 470–520 MHz
- STUBBY ANTENNAS**
- FA-SC56VS: 150–162 MHz
 - FA-SC57VS: 160–174 MHz
 - FA-SC73US: 450–490 MHz
- HIGH GAIN ANTENNAS**
- FA-SC62V: 150–160 MHz
 - FA-SC63V: 155–165 MHz
- CUT ANTENNAS**
- FA-SC61VC: 136–174 MHz
 - FA-SC61UC: 380–520 MHz

CHARGER ADAPTER
 • AD-122
 AD-122 charger adapter is supplied with the BC-197, depending on BC-197's version.

Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in Japan, the United States, the United Kingdom, Germany, France, Spain, Russia, Australia, New Zealand and/or other countries. IDAS and the IDAS logo are trademarks of Icom Incorporated. NXDN is a trademark of Icom Incorporated and JVC KENWOOD Corporation. All trademarks are the properties of their respective holders.

Icom Inc. 1-1-32, Kami-minami, Hirano-Ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013 www.icom.co.jp/world

Count on us!

Icom America Inc.
 12421 Willows Road NE,
 Kirkland, WA 98034, U.S.A.
 Phone: +1 (425) 454-8155
 Fax: +1 (425) 454-1509
 E-mail: sales@icomamerica.com
 URL: <http://www.icomamerica.com>

Icom (Europe) GmbH
 Communication Equipment
 Auf der Krautweide 24
 65812 Bad Soden am Taunus, Germany
 Phone: +49 (6196) 76685-0
 Fax: +49 (6196) 76685-50
 E-mail: info@icom-europe.com
 URL: <http://www.icomeurope.com>

Icom France s.a.s.
 Zac de la Plaine,
 1 Rue Brindejonc des Moulinais, BP 45804,
 31505 Toulouse Cedex 5, France
 Phone: +33 (5) 61 36 03 03
 Fax: +33 (5) 61 36 03 00
 E-mail: icom@icom-france.com
 URL: <http://www.icom-france.com>

Asia Icom Inc.
 6F No. 68, Sec. 1 Cheng-Teh Road,
 Taipei, Taiwan, R.O.C.
 Phone: +886 (02) 2559 1899
 Fax: +886 (02) 2559 1874
 E-mail: sales@asia-icom.com
 URL: <http://www.asia-icom.com>

Your local distributor/dealer:

Icom Canada
 Glenwood Centre #150-6165
 Highway 17A, Delta, B.C.,
 V4K 5B8, Canada
 Phone: +1 (604) 952-4266
 Fax: +1 (604) 952-0090
 E-mail: info@icomcanada.com
 URL: <http://www.icomcanada.com>

Icom Spain S.L.
 Ctra. Rubi, No. 88 "Edificio Can Castanyer"
 Bajos A 08174, Sant Cugat del Valles,
 Barcelona, Spain
 Phone: +34 (93) 590 26 70
 Fax: +34 (93) 589 04 46
 E-mail: icom@icomspain.com
 URL: <http://www.icomspain.com>

Icom (Australia) Pty. Ltd.
 Unit 1 / 103 Garden Road,
 Clayton, VIC 3168 Australia
 Phone: +61 (03) 9549 7500
 Fax: +61 (03) 9549 7505
 E-mail: sales@icom.net.au
 URL: <http://www.icom.net.au>

Shanghai Icom Ltd.
 No.101, Building 9, Caifuxingyuan Park,
 No.188 Maoting Road, Chedun Town,
 Songjiang District, Shanghai, 201611, China
 Phone: +86 (021) 6153 2768
 Fax: +86 (021) 5765 9987
 E-mail: bjicom@bjicom.com
 URL: <http://www.bjicom.com>

Icom Brazil
 Rua Itororó, 444 Padre Eustáquio
 Belo Horizonte MG,
 CEP: 30720-450, Brazil
 Phone: +55 (31) 3582 8847
 Fax: +55 (31) 3582 8987
 E-mail: sales@icombrasil.com

Icom (UK) Ltd.
 Blacksole House, Altira Park,
 Herne Bay, Kent, CT6 6GZ, U.K.
 Phone: +44 (0) 1227 741741
 Fax: +44 (0) 1227 741742
 E-mail: info@icomuk.co.uk
 URL: <http://www.icomuk.co.uk>

Icom New Zealand
 39C Rennie Drive, Airport Oaks,
 Auckland, New Zealand
 Phone: +64 (09) 274 4062
 Fax: +64 (09) 274 4708
 E-mail: inquiries@icom.co.nz
 URL: <http://www.icom.co.nz>